

RF Filters for Cellular Phones

Series/Type: B4121

The following products presented in this data sheet are being withdrawn.

Ordering Code	Substitute Product		Deadline Last Orders	Last Shipments
B39941B4121U510	B39941B4124U410	2009-04-03	2009-07-15	2009-10-15

For further information please contact your nearest EPCOS sales office, which will also support you in selecting a suitable substitute. The addresses of our worldwide sales network are presented at www.epcos.com/sales.

公TDK



Pin configuration

2	Input, unbalanced
1, 3	Input ground
4, 6	Output, balanced
5	To be grounded
1, 3, 5	Case ground



Туре	Ordering code	Marking and Package according to	Packing according to
B4121	B39941-B4121-U510	C61157-A7-A68	F61074-V8089-Z000

Electrostatic Sensitive Device (ESD)

Maximum ratings

Operable temperature range	Т	- 40 / + 85	°C	
Storage temperature range	T _{stg}	– 40 / + 85	°C	
DC voltage	V _{DC}	3	V	
Input power max.	P _{IN}			source impedance 50 Ω ,
880 915 MHz		18	dBm	load impedance 150 Ω ,
17051785 MHz		18	dBm	CW input for min. 2000 h

☆TDK

SAW Components		B4121
Low-Loss Filter for Mobile Commu	inication	942,50 MHz
Data Sheet	SMD	
Characteristics		

Operating temperature range:	T = 25+-2 °C
Terminating source impedance:	$Z_{\rm S}$ = 50 Ω
Terminating load impedance:	<i>Z</i> _L = 150 Ω 80 nH

						min.	typ.	max.	
Center fr	equency				f _C		942,5	—	MHz
Maximun	n insertion at	Honusti	o n		Q				
Waximun	in insertion at		960,0	MHz	α_{max}		2,8	3,2	dB
		020,0	000,0	101112			2,0	0,2	
Amplitud	le ripple (p-p))			Δα				
-		925,0	960,0	MHz			1,0	1,4	dB
Attenuati	ion				α				
	-	0,0	600,0	MHz		60	70		dB
		600,0	880,0	MHz		50	55		dB
		880,0	905,0	MHz		30	38		dB
		905,0	915,0	MHz		18	23		dB
		980,0	1000,0	MHz		21	23	_	dB
		1000,0	1025,0	MHz		30	37	_	dB
		1025,0	1050,0	MHz		35	40	_	dB
		1050,0	1500,0	MHz		50	57	_	dB
		1500,0	2130,0	MHz		45	55		dB
		2130,0	3000,0	MHz		40	48		dB
		•	4050,0	MHz		35	41		dB
		4050,0	5700,0	MHz		23	30		dB
Symmetr	ry in band								
•	ed to the mate	ched ope	erating conc	lition)					
	S ₃₁ / S ₂₁	925,0	960,0	MHz		-1,8	0	1,2	dB
i	arg(S ₃₁ /S ₂₁)	925,0	960,0	MHz		170	180	192	o

☆TDK

SAW Components					B4121
Low-Loss Filter for Mobile Com	munication			942,	50 MHz
Data Sheet	SMD				
Characteristics					
Operating temperature range:	T = -10 to				
Terminating source impedance: Terminating load impedance:	$Z_{\rm S} = 50 \ \Omega$ $Z_{\rm L} = 150 \ \Omega$		l		
		min.	typ.	max.	1
				max.	
Center frequency	f _C		942,5		MHz

Center frequency			f _C	—	942,5	—	MHz
Maximum insertion attenuat			$lpha_{max}$				
925,0	960,0	MHz			3,0	3,8	dB
Amplitude ripple (p-p)			Δα				
925,0	960,0	MHz		—	1,2	2,0	dB
Attenuation			α				
0,0		MHz		60	70	—	dB
600,0		MHz		50	55	—	dB
880,0	905,0	MHz		28	33	—	dB
905,0	915,0	MHz		18	21	—	dB
980,0	1000,0	MHz		20	22	—	dB
1000,0	1025,0	MHz		30	37	—	dB
1025,0	1050,0	MHz		35	40	—	dB
1050,0	1500,0	MHz		50	57	—	dB
1500,0	2130,0	MHz		45	55	—	dB
2130,0	3000,0	MHz		40	48	—	dB
3000,0	4050,0	MHz		35	41		dB
4050,0	5700,0	MHz		23	30		dB
Symmetry in band							
(referenced to the matched op	erating cond	lition)					
S ₃₁ / S ₂₁ 925,0	960,0	MHz		-2,3	0	1,2	dB
arg(S ₃₁ /S ₂₁) 925,0	960,0	MHz		170	180	192	o

⇔TDK

SAW Components		B4121
Low-Loss Filter for Mobile Co	mmunication	942,50 MHz
Data Sheet	SMD	
Characteristics		

Operating temperature range:	$T = -40 \text{ to } +85 \degree \text{C}$
Terminating source impedance:	$Z_{\rm S}$ = 50 Ω
Terminating load impedance:	<i>Z</i> _L = 150 Ω 80 nH

					min.	typ.	max.	
Center frequency				f _C	_	942,5	_	MHz
Maximum insertion atten	uatio	on		α_{max}				
92	25,0	960,0	MHz	max	_	3,4	4,2	dB
Amplitude ripple (p-p)				Δα				
92	25,0	960,0	MHz		_	1,8	2,6	dB
Attenuation				α				
	0,0	600,0	MHz		60	70		dB
60	0,0	880,0	MHz		50	55		dB
88	30,0	905,0	MHz		28	33		dB
90)5,0	915,0	MHz		18	21	_	dB
98	30,0	1000,0	MHz		19	21		dB
100	0,0	1025,0	MHz		30	37	_	dB
102	25,0	1050,0	MHz		35	40	_	dB
105	50,0	1500,0	MHz		50	57	_	dB
150	0,0	2130,0	MHz		45	55		dB
213	80,0	3000,0	MHz		40	48	_	dB
300	0,0	4050,0	MHz		35	41		dB
405	50,0	5700,0	MHz		23	30	-	dB
Symmetry in band								
(referenced to the matched	d ope	erating conc	lition)					
S ₃₁ / S ₂₁ 92	25,0	960,0	MHz		-2,6	0	1,2	dB
arg(S ₃₁ /S ₂₁) 92	25,0	960,0	MHz		170	180	192	0

公TDK





Transfer function (wideband)



6

☆TDK

SAW Components		B4121
Low-Loss Filter for Mobile Communication		942,50 MHz
Data Sheet	SMD	

Published by EPCOS AG Surface Acoustic Wave Components Division, SAW MC WT P.O. Box 80 17 09, 81617 Munich, GERMANY

© EPCOS AG 2002. Reproduction, publication and dissemination of this brochure and the information contained therein without EPCOS' prior express consent is prohibited.

Purchase orders are subject to the General Conditions for the Supply of Products and Services of the Electrical and Electronics Industry recommended by the ZVEI (German Electrical and Electronic Manufacturers' Association), unless otherwise agreed.

This brochure replaces the previous edition.

For questions on technology, prices and delivery please contact the Sales Offices of EPCOS AG or the international Representatives.

Due to technical requirements components may contain dangerous substances. For information on the type in question please also contact one of our Sales Offices.

