## **Fast Recovery Rectifier**



### **CFRB301 ~ CFRB307**

Forward Current: 3.0 Amp

Reverse Votlage: 50 ~ 1000 Volts

#### **Features**


- Glass Passivated Die Construction
- Fast Recovery Time for High Efficiency
- Low Forward Voltage Drop and High Current Capability
- Surge Overload Rating to 100A Peak
- Ideally Suited for Automatic Assembly

#### **Mechanical Data**

- Case: Molded Plastic
- Case Material: UL Flammability Classification Rating 94V-0
- Moisture sensitivity: Level 1 per J-STD-020C
- Terminals: Solder Plated Terminial Solderable per MIL-STD-202, Method 208
- Also Available in Lead Free Plating (Matte Tin Finish)
- Polarity: Cathode Band or Cathode Notch
- Weight: SMB 0.093 grams (approx)



SMB



#### MAXIMUM RATINGS AND ELECTRICAL CHARACTERISTICS

| Characteristic   | Syml  | ool CFRB<br>301   | CFRB<br>302 | CFRB<br>303 | CFRB<br>304 | CFRB<br>305 | CFRB<br>306 | CFRB<br>307 | Unit |
|--|---|-------------------|-------------|-------------|-------------|-------------|-------------|-------------|------|
| Peak Repetitive Reverse Voltage<br>Working Peak Reverse Voltage<br>DC Blocking Voltage                           | V <sub>RRI</sub><br>V <sub>RW</sub><br>V <sub>R</sub> | м 50              | 100         | 200         | 400         | 600         | 800         | 1000        | V    |
| RMS Reverse Voltage  | V <sub>R(RN</sub>                                     | <sub>IS)</sub> 35 | 70          | 140         | 280         | 420         | 560         | 700         | V    |
| Average Rectified Output Current @ T <sub>T</sub> =  | 75 °C l₀  |                   | 3.0         |             |             |             |             |             | Α    |
| Non-Repetitive Peak Forward Surge Current<br>8.3ms Single half sine-wave Superimposed on Rated<br>(JEDEC Method) | d Load I <sub>FSN</sub>                               | 1                 | 100         |             |             |             | А           |             |      |
| Forward Voltage @ I <sub>F</sub> =   | 3.0A V <sub>FN</sub>                                  | 4                 | 1.3         |             |             |             |             | V           |      |
| Peak Reverse @ TA = at Rated DC Blocking Voltage @ TA = 1  |   |                   | 5.0<br>250  |             |             |             |             |             | μА   |
| Maximum Recovery Time (Note 3)   | t <sub>rr</sub>                                       |                   | 150         |             |             | 250         | 500         |             | ns   |
| Typical Junction Capacitance (Note 2)  |   |                   | 50          |             |             |             |             |             |      |
| Typical Thermal Resistance Junction to Terminal (Note 1)   |   | т                 | 25          |             |             |             |             |             |      |
| Operating and Storage Temperature Range  |   | TG                | -65 to +150 |             |             |             |             |             |      |

1. Thermal resistance: junction to terminal, unit mounted on PC board with 5.0 mm (0.013 mm thick) copper pad as heat sink.

- 2. Measured at 1.0MHz and applied reverse voltage of 4.0V DC.
- 3. Reverse recovery test conditions:  $I_F = 0.5A$ ,  $I_R = 1.0A$ ,  $I_{rr} = 0.25A$ . See figure 5.

# **Fast Recovery Rectifier**



### **CFRB301 ~ CFRB307**




Fig. 5 Reverse Recovery Time Characteristic and Test Circuit

Set time base for 50/100 ns/cm

1. Rise Time = 7.0ns max. Input Impedance =  $1.0M\Omega$ , 22pF.

2. Rise Time = 10ns max. Input Impedance =  $50\Omega$ .