Panasonic

Surface Mount Type

Series: EP(Thin Type)

Features

- The industry minimum size 1.0 mm in height
- Reflow soldering method available (260 ° C)
- RoHS directive compliant

Recommended Applications

• RTC back-u p in thin and light devices such as mobile phones, smart phones and tablet PC

Specifications

Category Temp. Range	–10 °C to +60 °C							
Maximum Operating Voltage	3.3 V DC							
Nominal capacitance	0.03 F							
Stability at Low and High Tmperature		Lower category temp. (–10 $^\circ$ C)	Upper category temp. (+60 $^{\circ}$ C)					
	Capacitance change	\pm 30 % of initial measured value at 20 $^\circ$ C	\pm 30 % of initial measured value at 20 $^\circ$ C					
	Internal resistance	<10 times of initial measured value at 20 ° C	350 Ω or less					
Endurance	After 250 hours application of 3.3 V at +60 ° C							
	Capacitance change	\pm 30 % of initial measured value at 20 $^\circ$ C						
	Internal resistance	$4 \text{ k}\Omega$ or less						
Shelf Life	After 500 hours strage at +60 ° C without load (voltage)							
	Capacitance change	\pm 30 % of initial measured value at 20 $^\circ$ C						
	Internal resistance	1 kΩ or less						

Discontinue

Dimensions in mm(not to scale)

(Unit : mm) Terminal:Y 80.00 5 40 1 45+02 0 Ma .0±0. 3 85 Max

Standard Products

Maximum Operating Voltage (V.DC)	Capacitance (F)		Internal resistance (Initial specified value) (Ω) at 1 kHz	Maximum discharging current (µA)	Part number	Mass (g)	Min. Packaging Q'ty (pcs)
3.3	0.03	– 20% to +80%	⊲350	5	EECEP0F303Y	0.06	5000

The re-flow condition / taping dimensions are explained on EE210, EE211 of our catalog.

Note : 1. Do not use reflow soldering when cell voltage is above 0.3 V.

2. When the capacitor is being used in a high temperature and high humidity environment for a long period, and will not affectany electrical characteristics of the capacitor.

3: EP series is a small capacitor that developed for the RTC backup of cellular phone. Therefore, there is a possibility that it will not be able to back up in short term depend on using condition. Please contact us before you use it

